

NEMA Configurations for General-Purpose Nonlocking Plugs and Receptacles

Wiring/Voltage		15 Ampere		20 Ampere		30 Ampere		50 Ampere		60 Ampere	
		Receptacle	Plug	Receptacle	Plug	Receptacle	Plug	Receptacle	Plug	Receptacle	Plug
2 Pole 2 Wire	125V	1	1-15R	1-15P							
	250V	2		2-15P	2-20R	2-20P	2-30R	2-30P			
2 Pole 3 Wire Grounding	125V	5	5-15R	5-15P	5-20R	5-20P	5-30R	5-30P	5-50R	5-50P	
	250V	6	6-15R	6-15P	6-20R	6-20P	6-30R	6-30P	6-50R	6-50P	
	277V/AC	7	7-15R	7-15P	7-20R	7-20P	7-30R	7-30P	7-50R	7-50P	
	347V/AC	24	24-15R	24-15P	24-20R	24-20P	24-30R	24-30P	24-50R	24-50P	
3 Pole 3 Wire	125/250V	10			10-20R	10-20P	10-30R	10-30P	10-50R	10-50P	
	3Ø 250V	11	11-15R	11-15P	11-20R	11-20P	11-30R	11-30P	11-50R	11-50P	
3 Pole 4 Wire Grounding	125/250V	14	14-15R	14-15P	14-20R	14-20P	14-30R	14-30P	14-50R	14-50P	14-60R
	3Ø 250V	15	15-15R	15-15P	15-20R	15-20P	15-30R	15-30P	15-50R	15-50P	15-60R
4 Pole 4 Wire	3ØY 120/208V	18	18-15R	18-15P	18-20R	18-20P	18-30R	18-30P	18-50R	18-50P	18-60R

NEMA Configurations for Locking-Type Plugs and Receptacles

Wiring/Voltage		15 Ampere		20 Ampere		30 Ampere	
		Receptacle	Plug	Receptacle	Plug	Receptacle	Plug
2 Pole 2 Wire	125V	L1	L1-15R	L1-15P			
	250V	L2			L2-20R	L2-20P	
2 Pole 3 Wire Grounding	125V	L5	L5-15R	L5-15P	L5-20R	L5-20P	L5-30R
	250V	L6	L6-15R	L6-15P	L6-20R	L6-20P	L6-30R
	277V/AC	L7	L7-15R	L7-15P	L7-20R	L7-20P	L7-30R
	347V/AC	L24			L24-20R	L24-20P	
	480V/AC	L8			L8-20R	L8-20P	L8-30R
	600V/AC	L9			L9-20R	L9-20P	L9-30R